

DMA6112 120W Amplifier

DMA6112 120W 6 Channels Digital Audio Matrix Amplifier with Remote Control

- With a 4.3" resistive touch screen and a push-button power switch.
- Support 100V constant voltage function, configurable through the system.
- Chime function operable via the touch screen, with chimes and SIREN alarm sources changeable through USB.
- With 1×3.81mm Phoenix connector (1P of 7P) for FM antenna.
- With 1×3.81mm Phoenix connector (2P of 7P) for EMC IN.
- With 1×3.81mm Phoenix connector (2P of 7P) for MUTE.
- With 1×3.81mm Phoenix connector for MONITOR SPEAKER OUTPUT, to monitor signal output, linked with zone volume.
- With 6×2-pin 5.08mm terminal block power output interfaces.
- With one independent Bluetooth antenna.
- Designed for AC220-240V power supply.

Power	120 W
-------	-------



Ətraflı

Model	DMA6112
AUX Input Sensitivity	AUX1=AUX2=775±100mV
MIC Input Sensitivity	MIC1=MIC2=5±1mV
LINE Input Sensitivity	LINE1=LINE2=350±50mV
Output Power	120W*6
Distortion at Rated Power (Within Frequency Response Range)	95V<1% 100V<5%
Microphone S/N Ratio A-Weighted	≥71dB
Line S/N Ratio A-Weighted	≥76dB
Line Input Frequency Response	80Hz-15kHz (under normal operating conditions ±3dB)

Overload Source Electromotive Force	≥14dB (constant voltage)
Operating Voltage	AC220-240V
Tone Adjustment Range	Bass: ±10dB (100Hz), Treble: ±10dB (10kHz), both with an error of ±2dB
LINE OUT Output Level	1000±100mV
MIC1-2 Phantom Power	48V±5V
Operating Temperature	-10-50℃
Package Dimensions	535×540×155mm
Machine Dimensions	483×353×88mm
Gross Weight	8.45kg
Net Weight	6.95kg