

DMA60U Digital Amplifier

DMA60U 60W Digital Mixer Amplifier with USB /Bluetooth /FM/Chime/Siren/4 Mic(With PP and DC24V)

- Segment LCD screen
- With built-in Bluetooth, FM and USB function
- Master Volume Control & separate control
- MUTE & SIREN short circuit trigger
- Wireless Remote Controller to control
- With 3 MIC IN, 1 EMC IN, 2 AUX IN, 1 AUX OUT
- Priority level: MUTE>EMC=Alarm=Chime>MIC1>Others

Power	60 W
-------	------



Model	DMA60U
Power Supply	AC110-240V 50/60Hz
MIC1 Input Sensitivity	10mV 1mv
MIC2 Input Sensitivity	10mV 1mv
AUX1 IN Sensitivity	350mV 50mv
AUX2 IN Sensitivity	350mV 50mv
EMC IN Sensitivity	350mV and 50mv
MIC Frequency Response	120Hz~12kHz (±3dB)
AUX Frequency Response	80Hz~15kHz (±3dB)
Distortion	<1%
Treble	10dB (±2)
Bass	10dB (±2)
Operating Temperature	-10-50℃
Relative Humidity	20%-80%

Rated Output Power	AC 110-240V	60W
	DC24V	60W
Output Port Voltage		4-16Ω, 70V, 100V (constant voltage output)
Unit Dimensions (D×W×H)		430×280×88mm
Package Dimensions		500×450×165mm
Net Weight		3.8KG
Gross Weight		5KG