

DMA120U Digital Amplifier

DMA120U 120W Digital Mixer Amplifier with USB/Bluetooth /FM/Chime/Siren/4 Mic(With PP and DC24V)

- Rated power 120W
- 70V/100V & 4-16Ω speaker output
- Audio input: 3 Mic, 2 AUX, 2 EMC
- Support USB/FM/Bluetooth function
- With 1 AUX output for power extension
- With 1 Pre-out interface for audio processor
- With rack mount handles for standard 19” rack
- Mic 2-3 with phantom power 48V and independent gain adjustment
- Individual volume control for Mic and Aux input
- With Bass/Treble/Master volume control
- Support EMC input/Siren/Mute
- Priority: MUTE>EMC=Alarm=Chime>MIC1>Others
- Support IR remote controller
- Power supply: AC110V -240V/50Hz -60Hz or DC24V
- For Use Vehicle/Building

Power	120 W
-------	-------



Ətraflı

Model	DMA120U
Power Supply	AC110-240V 50/60Hz
MIC1 IN Sensitivity	10mV ±1mv
MIC2 IN Sensitivity	10mV±1mv
AUX1 IN Sensitivity	350mV±50mv
AUX2 IN Sensitivity	350mV±50mv
EMC IN Sensitivity	350mV±50mv
MIC Frequency Response	120Hz□12kHz (±3dB)

AUX Frequency Response		80Hz~15kHz (±3dB)
Distortion		<1%
Treble		10dB (±2)
Bass		10dB (±2)
Working Temperature		-10-50℃
Relative Humidity		20%-80%
Rated Output Power	AC 110-240V	120W
	DC24V	60W
Port Output Voltage		4-16Ω,70V,100V (constant-voltage output)
Machine Dimensions (D×W×H)		430×280×88mm
Package Dimensions		500×450×165mm
Net Weight		4.6KG
Gross Weight		5.8KG