

DMA250U Digital Amplifier

DMA250U 250W Digital Mixer Amplifier with USB/Bluetooth /FM/Chime/Siren/4 Mic(With PP and DC24V)

Segment LCD screen
 With built-in Bluetooth, FM and USB function
 Master Volume Control & separate control
 MUTE & SIREN short circuit trigger
 Wireless Remote Controller to control
 With 3 MIC IN, 1 EMC IN, 2 AUX IN, 1 AUX OUT
 Priority level: MUTE>EMC=Alarm=Chime>MIC1>Others

Power	250 W
-------	-------



Detailed

Model	DMA250U
Power Supply	AC110-120V or 200-240V 50/60Hz
MIC1 IN Sensitivity	10mV ±1mv
MIC2 IN Sensitivity	10mV±1mv
AUX1 IN Sensitivity	350mV±50mv
AUX2 IN Sensitivity	350mV±50mv
EMC IN Sensitivity	350mV±50mv
MIC Frequency Response	120Hz□12kHz (±3dB)
AUX Frequency Response	80Hz□15kHz (±3dB)
Distortion	<1%
Treble	10dB (±2)
Bass	10dB (±2)
Working Temperature	-10-50°C

Relative Humidity		20%-80%
Rated Output Power	AC 110-240V	250W
	DC24V	60W
Port Output Voltage		4-16 Ω ,70V,100V (constant-voltage output)
Machine Dimensions (D×W×H)		430×330×88mm
Package Dimensions		500×500×165mm
Net Weight		6.8KG
Gross Weight		8.3KG