

DMA350U Digital Amplifier

DMA350U 350W Digital Mixer Amplifier with USB/Bluetooth /FM/Chime/Siren/4 Mic(With PP and DC24V)

- With a segment code tube screen, and intuitive display, more convenient for users to use
- With built-in Bluetooth, FM and USB functions
- With 3 MIC IN, 1 EMC IN, 2 AUX IN, 1 AUX OUT
- Support 100V and 70V constant voltage output, and 4Ω□16Ω constant resistance output
- Can be controlled by the infrared remote controller
- With priority function, and the priority is MUTE>EMC=Alarm=Chime>MIC1>Others (When there is an alarm, no chime can be output)
- With master volume control, independent volume control of MIC and AUX, and TREBLE and Bass volume control
- With the SIREN short circuit trigger function, which can be remotely controlled by this machine or controlled by other devices, with independent alarm output
- With MUTE short circuit trigger function, which can be remotely controlled by this machine or controlled by other devices
- With 1 EMC IN, which can be used to input alarm signals from other devices to this machine
- With power-off memory function

Power	350 W
-------	-------



Ətraflı

Model	DMA350U
Power Supply	AC110-AC115V or AC220-230V 50/60Hz
MIC1 IN Sensitivity	10mV ±1mv
MIC2 IN Sensitivity	10mV±1mv
AUX1 IN Sensitivity	350mV±50mv
AUX2 IN Sensitivity	350mV±50mv
EMC IN Sensitivity	350mV±50mv
MIC Frequency Response	120Hz□12kHz (±3dB)
AUX Frequency Response	80Hz□15kHz (±3dB)

Distortion		<1%
Treble		10dB (±2)
Bass		10dB (±2)
Working Temperature		-10-50°C
Relative Humidity		20%-80%
Rated Output Power	AC 110-240V	350W
	DC24V	175W
Port Output Voltage		4-16Ω,100V (constant-voltage output)
Machine Dimensions (D×W×H)		430×380×88mm
Package Dimensions		550×500×165mm
Net Weight		6.1KG
Gross Weight		7.6KG