

DMA350U Digital Amplifier

DMA350U 350W Digital Mixer Amplifier with USB/Bluetooth /FM/Chime/Siren/4 Mic(With PP and DC24V)

With a segment code tube screen, and intuitive display, more convenient for users to use

With built-in Bluetooth, FM and USB functions

With 3 MIC IN, 1 EMC IN, 2 AUX IN, 1 AUX OUT

Support 100V and 70V constant voltage output, and 4Ω-16Ω constant resistance output

Can be controlled by the infrared remote controller

With priority function, and the priority is MUTE>EMC=Alarm=Chime>MIC1>Others (When there is an alarm, no chime can be output)

With master volume control, independent volume control of MIC and AUX, and TREBLE and Bass volume control

With the SIREN short circuit trigger function, which can be remotely controlled by this machine or controlled by other devices, with independent alarm output

With MUTE short circuit trigger function, which can be remotely controlled by this machine or controlled by other devices

With 1 EMC IN, which can be used to input alarm signals from other devices to this machine

With power-off memory function

Power	350 W
-------	-------



Detailed

Model	DMA350U
Power Supply	AC110-AC115V or AC220-230V 50/60Hz
MIC1 IN Sensitivity	10mV ±1mv
MIC2 IN Sensitivity	10mV±1mv
AUX1 IN Sensitivity	350mV±50mv
AUX2 IN Sensitivity	350mV±50mv
EMC IN Sensitivity	350mV±50mv
MIC Frequency Response	120Hz-12kHz (±3dB)
AUX Frequency Response	80Hz-15kHz (±3dB)

Distortion	<1%	
Treble	10dB (± 2)	
Bass	10dB (± 2)	
Working Temperature	-10-50°C	
Relative Humidity	20%-80%	
Rated Output Power	AC 110-240V	350W
	DC24V	175W
Port Output Voltage	4-16Ω, 100V (constant-voltage output)	
Machine Dimensions (D×W×H)	430×380×88mm	
Package Dimensions	550×500×165mm	
Net Weight	6.1KG	
Gross Weight	7.6KG	

Daytech.Az