

DMA6350U Digital Amplifier

DMA6350U 350W 6 Zones Digital Mixer Amplifier with Remote Paging Station

- 70V/100V & 4-16Ω speaker output
- Rated power: 350W
- Input source: 4 Mic, 4 AUX and USB/FM/Bluetooth/TF
- Support 6 remote paging microphones
- With 19" rack mount handles
- Phoenix port for Mic2-4 input, Line2 input, EMC input
- Mute and Siren
- Mic 2-4 with phantom power 48V
- Individual volume control and Bass/Treble adjustment
- Remote Mic>Mic2-Mic4/AUX input/Bluetooth/FM/USB
- Protection: Overload, Clipping, Short circuit and temperature protection
- Power supply: AC220V-230V/50Hz/60Hz or DC24V

Power	350 W
-------	-------



Detailed

Model		DMA6350U
Power		AC220-230V 50/ 60Hz
Input Sensitivity	MIC1	5mV ±1mv (Balanced XLR Input)
	MIC2/MIC3/MIC4	5mV ±1mv (Unbalanced Phoenix Jacks)
	AUX1	350mV±50mv (Unbalanced RCA Input)
	AUX2	350mV ±50mv (Unbalanced Phoenix Jacks)
	EMC	350mV ±50mv (Unbalanced Phoenix Jacks)

MIC Frequency Response	120Hz□12kHz (±3dB)
AUX Frequency Response	80Hz□15kHz (±3dB)
THD	<1%
Treble Adjustment Range	10dB□±2□
BASS Adjustment Range	10dB□±2□
Phantom Power	+48V
Rated Output Power	350W
Output Voltage of Port	4-16Ω,70V,100V(fixed voltage output)
Current	3A
Protection	F6.3AL
Machine Dimension(D×W×H)	430×390×88mm
Package Dimension:	545×500×165mm
Net Weight	9KG
Gross Weight	10.2KG