

DMA6500U Digital Amplifier

DMA6500U 500W 6 Zones Integrated Mixing Amplifier with Remote Paging Station

70V/100V & 4-16Ω speaker output

Rated power: 500W

Input source: 4 Mic, 4 AUX and USB/FM/Bluetooth/TF

Support 6 remote paging microphones

With 19" rack mount handles

Phoenix port for Mic2-4 input, Line2 input, EMC input

Mute and Siren

Mic 2-4 with phantom power 48V

Individual volume control and Bass/Treble adjustment

Remote Mic>Mic2-Mic4/AUX input/Bluetooth/FM/USB

Protection: Overload, Clipping, Short circuit and temperature protection

Power supply: AC220V-230V/50Hz/60Hz or DC24V

Power	500 W
-------	-------



Detailed

Model	DMA6500U	
Power	AC220-230V 50/ 60Hz	
Input Sensitivity	MIC1	5mV ±1mv (Balanced XLR Input)
	MIC2/MIC3/MIC4	5mV ±1mv (Unbalanced Phoenix Jacks)
	AUX1	350mV±50mv (Unbalanced RCA Input)
	AUX2	350mV ±50mv (Unbalanced Phoenix Jacks)

	EMC	350mV \pm 50mv (Unbalanced Phoenix Jacks)
MIC Frequency Response		120Hz \square 12kHz (\pm 3dB)
AUX Frequency Response		80Hz \square 15kHz (\pm 3dB)
THD		<1%
Treble Adjustment Range		10dB \square \pm 2 \square
BASS Adjustment Range		10dB \square \pm 2 \square
Phantom Power		+48V
Rated Output Power		500W
Output Voltage of Port		4-16 Ω ,70V,100V(fixed voltage output)
Current		3A
Protection		F6.3AL
Machine Dimension(D \times W \times H)		430 \times 390 \times 88mm
Package Dimension:		545 \times 500 \times 165mm
Net Weight		10.1KG
Gross Weight		11.3KG