

PAVA9425E Amplifier

PAVA9425E 4 Zone Expansion Amplifier with Main / Backup Switching

4 zones speaker output (could be extended up to 128 zones)
 Built-in 1000W main amplifier and 1000W backup amplifier, with amplifier fault detection
 Support 2 balanced microphone inputs, 4 analog AUX inputs and 1 AUX output
 With master volume control and treble and bass control
 Support paging to specific zone without interrupting background music broadcasting
 With on/off buttons for an independent zone and all zones
 Support expansion amplifier address selection
 Support program source monitoring function
 Support remote computer detection and control
 Support speaker line detection and system detection
 4 channels dry contact trigger input/output, 4 channels DC24V override output
 Support AC220V and DC24V power supply

Power	1000 W
-------	--------



Detailed

Model	PAVA9425E	
Rated Output Power	$\geq 1000W (100V)$	
Input Sensitivity	EMC MIC	---

	MIC	5±0.5mV 10kΩ
	LINE	1000±100mV 10kΩ
Harmonic Distortion	EMC MIC	<1% 1kHz
	MIC	1%1khz
	LINE	<1% 1kHz
Frequency Response	EMC MIC	80Hz-15kHz (±3dB)
	MIC	1%1khz
	LINE	50Hz-18kHz (±3dB)
S/N Ratio	EMC MIC	>75dB (A weighted)
	MIC	1%1khz
	LINE	>80dB (A weighted)
EMC LINE AUX OUT	Output Voltage	1000mV
	Frequency Range	80Hz-15kHz±3dB
	Harmonic Distortion	<1% 1kHz
System Connection Control Contact Output/Input	System Fault Relay Output	Short circuit, no voltage
	Emergency Mode Relay Output	Short circuit, no voltage
	Fire Reset Input	Short circuit, t≥0.5S, no voltage
	4-Channel Dry Contact Output	Short circuit, no voltage
	4-Channel Dry Contact Input	Short Circuit Mode Level Mode

Working Power	AC	AC220V-230V/50-60Hz
	DC	DC 24V/34A
Package Dimensions (L*W*H)		625×635×165mm
Machine Dimensions (L*W*H)		428*430*88mm
Gross Weight		14kg
Net Weight		12.05kg

Daytech.Az