

EVAC-12KD Expansion Keypad

EVAC-12KD Expansion Keypad 12 Zone

- Each zone expansion keypad supports 12 zone selections.
- The keypad is used to expand the capacity of remote microphone for multiple-zones.
- Connecting one of these keypads to 12 zones or zone groups that can be selected.
- Up to 11 keypads can be added to an EVAC-500RM Remote Microphone.
- LEDs on the keypad indicate the active zones.
- 12 zone selection keys and 12 zone selection LEDs
- Total system capacity of 120 zones.
- Keypad internal line will be monitored, fault will be indicated by LED and buzzer.



Detailed

| Model | EVAC-12KD | |
|--------------------|---------------------------------|------|
| Description | Zone Expansion Keypad (36 Zone) | |
| Power Consumption | 3W | |
| Zone Capacity | 12 Zones | |
| System Capacity | 11 units of keypad | |
| Frequency Response | 80Hz~16kHz | |
| THD | ≤1% at RMS | 1KHz |
| S/N Ratio | >70dB | |
| Operating Temp | -20°C to +70°C | |
| Power Supply | DC5V, ±20% | |
| Humidity | <95% no condensation | |

| | |
|-----------|----------------|
| Dimension | 132(W)×150(H)× |
| Weight | 0.7kg |

Daytech.Az