DAYTECH.AZ

MP912 Mixer Amplifier

MP912 4x4 Matrix Mixer Amplifier

- Built-in 4 separate amplifier outputs, each channel RMS 120W
- 5 AUX inputs, 3 balanced Mic input with phantom power supply
- 4 remote paging stations, support cascaded linkage
- Each AUX and Mic input with volume and Bass & Treble control
- Each channel can play different audio source and has AUX output for power extension
- Support TEL input, built-in chime and one touch emergency alarm
- 70V/100V & 4-16 Ω flexible speaker output



Ətraflı

Model	MP912
Rated output power	120W×4
Loudspeaker output	4-16Ω, 70V, 100V
Input sensitivity and input impedance	AUX1, AUX2, AUX3: $(3\pm0.5\text{mV}/600\Omega) \sim (300\pm50\text{mV}/10\text{K}\Omega)$ balanced input; AUX4, AUX5: 300 ± 50 mV /10 K Ω unbalanced input; TEL: $300\pm50\text{mV}/10$ K Ω ; CALL STATION1, 2, 3: 2000 ± 100 mV/10K Ω balanced input
Tune	Bass 100Hz ±10±2 dB; Treble 10000H ±10±2dB;
Frequency response	90Hz~20kHz

Signal to noise ratio	≥75 dB
AUX14 output level	2000mV±300mV/600Ω balanced output
MP3	Play documents in the formats of MP3, WMA, WAC and ACC stored in 32GU disk or transferred byBluetooth
Dimension of equipment	483×440×132mm
(L×W×H mm)	
Dimension of packing	550×550×215mm
(L×W×H mm)	
Net weight	28kg
Gross weight	30.5kg

Daytech.Az