

MP912 Mixer Amplifier

MP912 4x4 Matrix Mixer Amplifier

- Built-in 4 separate amplifier outputs, each channel RMS 120W
- 5 AUX inputs, 3 balanced Mic input with phantom power supply
- 4 remote paging stations, support cascaded linkage
- Each AUX and Mic input with volume and Bass & Treble control
- Each channel can play different audio source and has AUX output for power extension
- Support TEL input, built-in chime and one touch emergency alarm
- 70V/100V & 4-16 Ω flexible speaker output

Power	120 W
-------	-------



Detailed

Model	MP912
Rated output power	120W×4
Loudspeaker output	4-16Ω, 70V, 100V
Input sensitivity and input impedance	AUX1, AUX2, AUX3: (3±0.5mV/600Ω) ~ (300±50mV /10KΩ) balanced input; AUX4, AUX5: 300±50 mV /10 KΩ unbalanced input; TEL: 300±50mV /10 KΩ; CALL STATION1, 2, 3: 2000±100 mV/10KΩ balanced input
Tune	Bass 100Hz ±10±2 dB; Treble 10000H ±10±2dB;
Frequency response	90Hz~20kHz

Signal to noise ratio	≥ 75 dB
AUX1---4 output level	2000mV \pm 300mV/600 Ω balanced output
MP3	Play documents in the formats of MP3, WMA, WAC and ACC stored in 32GU disk or transferred byBluetooth
Dimension of equipment (LxWxH mm)	483x440x132mm
Dimension of packing (LxWxH mm)	550x550x215mm
Net weight	28kg
Gross weight	30.5kg

Daytech.Az