

## Amplifier DS-USB-80A

DS-USB-80A Pa Amplifier

The broadcast power amplifier has 2 line and 2 microphone inputs

Built-in radio and MP3 player, SD card slot

TADS Power Amplifiers

Independent microphone volume control

Power	80 W
-------	------



### Detailed

<b>Model</b>	<b>DS-USB-80A</b>
Power Supply	AC220V/50HZ
Transmission Rate	10Mbps/100Mbps
Audio Format	MP3/MP2
Sampling Rate	8K ~ 256K
Bit Rate	8K ~ 512Kbps
EMC Input Sensitivity	775mV

Audio Mode	16-32 bit stereo CD quality
AUX Input Sensitivity	350mV
MIC Input Sensitivity	10mV
Rated Power	120W/240W/500W/700W
Standby Power Consumption	< 0.2W
Frequency Response	50Hz~18KHz 1/3dB
Harmonic Distortion	THD≤0.1%
Signal to noise Ratio	≥85dB
Output mode	4~16Ω constant resistance output, 70V/100V constant voltage output
Size	484*410*88mm
Ambient Temperature	-10°C ~ 65°C
Ambient Humidity	20% ~ 80% relative humidity, no condensation
Weight	11KG/17KG/19KG/21KG/23KG