

## Amplifier PA-5150USB

PA-5150USB Pa Amplifier

- ◆ 2-channel microphone, 3-channel line input, 6-channel independent control
- ◆ Each channel can independently load 75% of the total power
- ◆ 6 partitions independent volume control, all the way through
- ◆ Priority microphone 1 with silent intrusion function for emergencies broadcast
- ◆ Six partition output
- ◆ USB+FM+SD+Bluetooth+remote control+digital screen display
- ◆ Dimensions: 482\*390\*88MM

Power	150 W
-------	-------



### Detailed

<b>Model</b>	<b>PA-5150USB</b>
Type	Professional Amplifier
Rated Power	150W
Sensitivity	77.5MV
SNR	Mic>70dB , Line>76dB
Output Mode	4-16ohms/70V/100V

THD	<0.1%
FR	40hz-18KHZ±0.5DB
Muting Function	<p>MIC1 with Priority muting for emergency broadcast</p> <p>6 Zones mixing amplifier with MP3 player, USB/SD card</p> <p>With alarm function and LED display</p> <p>Independently control for treble and bass, master volume control</p> <p>Protection function of AC fuse, short circuit, overload, high temperature</p> <p>2 microphone inputs and 3 line input</p>
Dimensions	482*390*88mm
Sound Channel	1
Voltage	AC 220V