

## MP60UB Mini Digital Amplifier

MP60UB 60W Mini Digital Mixer Amplifier with USB & Bluetooth

- Built-in Bluetooth, FM, and USB functions
- 2 MIC inputs, 2 line inputs, 1 line output
- 2 EMC inputs (100V/375mV), 1 EMC output
- Support 100V/70V constant voltage output, and 4-16Ω constant resistance output
- Can be controlled by the infrared remote controller
- With the priority function, the priority is EMC/MIC1>AUX1/AUX2/MIC2
- With master volume control, individual volume control for MIC & LINE, treble, and bass volume control

Power	60 W
-------	------



### Ətraflı

Model	MP60UB
Power Supply	~110-240 50/60Hz
MIC1 Input Sensitivity	5.5mV±1mV
MIC2 Input Sensitivity	5.5mV±1mV
AUX1 Input Sensitivity	350mV±10%
AUX2 Input Sensitivity	350mV±10%
EMC Input Sensitivity	350mV±10%
MIC Frequency Response	200Hz~10kHz (±3dB)
AUX Frequency Response	100Hz~15kHz (±3dB)
Distortion	<1% 1KHZ
Treble Adjustment	10dB (±2)
Bass Adjustment	10dB (±2)

RatedOutput Power	60W
Interface OutputMode	70V, 100V (constant voltage output), 4-16Ω
Machine Size (D×W×H)	198×247×66mm
Package Size	302×343×121mm (1PC)
Maximum Package Size	355×630×283mm (4PCS)
Net Weight	2.6kg
Gross Weight	3.25kg (1PC)

---

[Daytech.Az](http://Daytech.Az)