

MP120UB Mini Digital Amplifier

MP120UB 120W Mini Digital Mixer Amplifier with USB & Bluetooth

- Built-in Bluetooth, FM, and USB functions
- 2 MIC inputs, 2 line inputs, 1 line output
- 2 EMC inputs (100V/375mV), 1 EMC output
- Support 100V/70V constant voltage output, and 4-16Ω constant resistance output
- Can be controlled by the infrared remote controller
- With the priority function, the priority is EMC/MIC1>AUX1/AUX2/MIC2
- With master volume control, individual volume control for MIC & LINE, treble, and bass volume control

Power	120 W
-------	-------



Detailed

Model	MP120UB
Power Supply	~110-240 50/60Hz
MIC1 Input Sensitivity	7mV±1mV
MIC2 Input Sensitivity	7mV±1mV
AUX1 Input Sensitivity	300mV±10%
AUX2 Input Sensitivity	300mV±10%
EMC Input Sensitivity	350mV±10%
MIC Frequency Response	100Hz~8kHz (±3dB)
AUX Frequency Response	80Hz~15kHz (±3dB)
Noise	≤6mV (4Ω load out)
Distortion	<1% 1KHZ
Treble Adjustment	10dB (±2)

Bass Adjustment	10dB (±2)
RatedOutput Power	120W
Interface OutputMode	70V, 100V (constant voltage output), 4-16Ω
Machine Size (D×W×H)	198×247×66mm
Package Size	302×343×121mm (1PC)
Maximum Package Size	355×630×283mm (4PCS)
Net Weight	3kg
Gross Weight	3.7kg (1PC)