

## DMA250U Digital Amplifier

DMA250U 250W Digital Mixer Amplifier with USB/Bluetooth /FM/Chime/Siren/4 Mic(With PP and DC24V)

Segment LCD screen  
 With built-in Bluetooth, FM and USB function  
 Master Volume Control & separate control  
 MUTE & SIREN short circuit trigger  
 Wireless Remote Controller to control  
 With 3 MIC IN, 1 EMC IN, 2 AUX IN, 1 AUX OUT  
 Priority level: MUTE>EMC=Alarm=Chime>MIC1>Others

Power	250 W
-------	-------



## Detailed

Model	DMA250U
Power Supply	AC110-120V or 200-240V 50/60Hz
MIC1 IN Sensitivity	10mV $\pm$ 1mv
MIC2 IN Sensitivity	10mV $\pm$ 1mv
AUX1 IN Sensitivity	350mV $\pm$ 50mv
AUX2 IN Sensitivity	350mV $\pm$ 50mv
EMC IN Sensitivity	350mV $\pm$ 50mv
MIC Frequency Response	120Hz $\square$ 12kHz ( $\pm$ 3dB)
AUX Frequency Response	80Hz $\square$ 15kHz ( $\pm$ 3dB)
Distortion	<1%
Treble	10dB ( $\pm$ 2)
Bass	10dB ( $\pm$ 2)
Working Temperature	-10-50°C

Relative Humidity		20%-80%
Rated Output Power	AC 110-240V	250W
	DC24V	60W
Port Output Voltage		4-16Ω, 70V, 100V (constant-voltage output)
Machine Dimensions (D×W×H)		430×330×88mm
Package Dimensions		500×500×165mm
Net Weight		6.8KG
Gross Weight		8.3KG

---

[Daytech.Az](http://Daytech.Az)