

Mini40 Bluetooth Amplifier

Mini40 2x20W Mini Bluetooth Amplifier (4-16Ω)

- Frame with rounded corners, elegant and moderate. With precision frosting process and surface oxidation process, and no rust
- Leading digital power amplification technology, differential input and output design, and two-stage filter processing circuit can ensure excellent SNR, achieving full-range high-fidelity stereo reproduction, and powerful low-frequency and clear high-frequency
- Safe and reliable, with over-temperature, over-current, and short-circuit protection, as well as soft-starting technology to effectively protect the speaker
- Easy to use, with two connection methods: Line and Bluetooth
- Wide voltage design, applicable worldwide



Ətraflı

Model	Mini40
Rated Power	2×20W/8Ω
Freq. Resp.	20Hz-20KHz
Distortion	≤0.3%
SNR	≥82dB
Matched Impedance	8Ω
LINE IN Sensitivity	0dB(1V)
LINE IN Impedance	≥10KΩ
BT Transmission	10m
BT Standard	BT2.1+EDR
Power Supply	220V/50Hz/60Hz
Net Weight	0.33KG
Gross Weight	0.35KG
Product Dimension	125mm ×100mm×35mm
Package Dimension	135mm ×110mm×45mm

