

Mini40 Bluetooth Amplifier

Mini40 2x20w mini Bluetooth amplifier (4-16Ω)

Frame with rounded corners, elegant and gentle. Precise freezing process and surface oxidation process and no rust. Leading digital power amplifier technology, differential input and output design and two-stage filter processing circuit can provide excellent SNR, full high-end stereo reproduction and strong low-frequency and clear high-frequency.

Safe and reliable, with over-temperature, over-current and short-circuit protection, as well as soft-start technology to effectively protect the speaker.

Easy to use, with two connection methods: Line and Bluetooth

Wide voltage design, applied worldwide



Detailed

Model	Mini40
Rated Power	2×20W/8Ω
Freq. Resp.	20Hz-20KHz
Distortion	0.3%
SNR	82dB
Matched Impedance	8Ω
LINE IN Sensitivity	0dB(1V)
LINE IN Impedance	10KΩ
BT Transmission	10m
BT Standard	BT2.1+EDR
Power Supply	220V/50Hz/60Hz
Net Weight	0.33KG
Gross Weight	0.35KG
Product Dimension	125mm ×100mm×35mm
Package Dimension	135mm ×110mm×45mm

