

EVAC-500TM Remote Microphone

EVAC-500TM EN54-16 Touch Screen Remote Microphone, which is used for voice alarm & evacuation system, live speech, pre-recorded message announcement, individual zone, group zone and all zone paging multiple modes for voice evacuation & paging system.

- 1.Touch screen remote microphone or call station
- 2.EN54-16 Certified remote microphone
- 3.Business & commercial zone live announcement use
- 4.Multiple zones, single zone & all zone paging
- 5.Each microphone of 120 zone capacity
- 6.Support 32 remote microphones of loop redundancy connection
- 7.The remote microphone unit is fully real time monitored
- 8.Support PPT and lock type two modes
- 9.Shielded CAT6 cable up to 600 meters
- 10.Power supply from EVAC-500 controller



Detailed

Model	EVAC-500TM
Description	Touch Screen Remote Microphone
Power Consumption	3W
Zone Capacity	120 Zones
Input	Line: 350mV, 10kΩ, Mic: 5mV, 600Ω
Frequency Response	80Hz~16kHz
THD	≤1% at RMS,1KHz
S/N Ratio	>70dB
Operating Temp	-20℃ to +70℃; <95% no condensation

Power Supply	DC24V, ±20%
Dimension	153×52×282 mm
Weight	1.3kg