

M2W Broadcast Kit

M2W is a set consisting of a DM835 in-wall stereo music amplifier and two ceiling DSP5011L speakers, the power of the kit is 20 watts. Perfect for streaming music in your room, small boutique, or office in a beauty salon, the DM835 is a convenient and efficient control center for your music, with an elegant look with a modern and luxurious design. A wide range of audio sources, including FM tuner, SD card, Bluetooth, USB, AUX1, AUX2 has a fast and convenient playback interface.

Power	20W
-------	-----



Detailed

Model	DM835
Output Power	2 x10W
Impedance	8Ω
Harmonic distortion	≤0.03%□1kHz,1W,8Ω
The ratio of signal to noise	□81dB
Frequency response	20Hz -20kHz
Memory card capacity	128MB-16GB
Audio format	MP3, WMA, WAV, FLAC, etc.
Bluetooth	BT2.1+EDR
Power supply	AC 100-240V/50-60Hz
Product dimension	86*86*38MM□L*W*H□
Speakers	
Model	DSP5011L
Unit Driver	6.5"*1

Effective frequency range	(140~18k) Hz
Rated power	6W
Impedance	8Ω
Maximum sound pressure level	98dB±2dB
Characteristic sensitivity (1m/1w)	93dB±2dB
Storage temperature	-25°C~+55°C
Outline dimension	185mm*69mm
Weight	0.75kg