


PA-200MX Stereo Pre-Amplifier

PA-200MX 11 Channel Stereo Mixer & Pre-Amplifier

- 11 inputs stereo mixer or stereo pre-amplifier
- 19" rack mount design of 1U height
- 6x balanced Mic/Line inputs, Aux 1-4 inputs and EMC input
- Individually Mic/Line switchable with 48V phantom power
- REC output and stereo balanced XLR outputs
- Input priority from high to low: Mic1>EMC>Mic2-5 or EMC>Mic1>Mic2-5
- 100V to 240V AC and 24V DC both power supply



Detailed

Model	PA-200MX
Description	11 Inputs Stereo Mixer
Input	6x balanced Mic/Line inputs, XLR, 600Ω, 5mV Aux 1-4 inputs, RCA, 10kΩ, 200mV EMC input, RCA 10kΩ, 200mV
Output	Stereo balanced XLR, 10kΩ, 0.775mV
Frequency Response	60-15KHz
THD	<0.01% at 1kHz
S/N Ratio	>70dB
Priority	Mic1>EMC>Mic2-5 or EMC>Mic1>Mic2-5
Power Consumption	15W
Power Supply	100V to 240V AC and 24V DC both power supply
Dimension	483 x 440 x 100mm
Weight	2.6kg

